

Technical Reference:

Voltage: AC110-220V 50-60HZ

Power: 80w

Light source: 9 PCS*3W 3IN1; 1PCS*30W 3IN1

Channel: 6CH

Control mode: auto, sound, master-slave, DMX512

Material: Plastic

LED Stage Lighting Operating Manual

9+1 Digit PAR Light RGB

■ RGB 3IN1 PAR



Please Read Over This Manual before Operating the Light Fixture

Thank you so much to choose this product; it is adopting the most advanced lamps, which is called LED lamps. It conquers a lot of disadvantages such as power wasting, short using life, high temperature, etc. It has advantages of power saving, long life (it can reach 60,000.00 hours in general circs), high brightness, fresh colors...It is the best stage illuminating and various effect decorative products.

Security:

1. Make sure the user voltage cannot higher or lower than the regulate value of the user manual.
2. Please take more attention while installing the fixtures. Avoid touching exposed AC cord, or will cause deadly accident.
3. When installing the fixtures, make sure the fixtures are not exposed in extremely hot, humid or dusty environment. Make sure the distance between the fixture and the lighted object is not less than 0.5 meter. Make sure there is no combustible or explosive object around 0.5 meters.
4. Please operate the light fixture after becoming very familiar with the functions. In most cases, the light fixture will be broken by incorrect operation. It won't allow laypeople to operate this light. Don't shake or anything rudely to the light fixture, or it will cause problems.

DMX512 Control:

6Channel Model

Channel	Channel data	Function instruction
CH1	0-255	Master dimming
CH2	0-255	Red dimming
CH3	0-255	Green dimming
CH4	0-255	Blue dimming
CH5	1-255	Strobe control
CH6	1-255	Master function + sound control

Digital Par User Manual

